METHOD OF CONTROLLING AN ELECTRONIC NON-VOLATILE MEMORY AND ASSOCIATED DEVICE

Field of the Invention

The present invention relates to non-volatile electronic memories, and in particular, to a method of controlling memory cells in an EEPROM that includes
5   setting a state of the memory cells.

Background of the Invention

EPROM devices that include floating gate transistors are electrically programmable but are not electrically erasable. These memory devices are
10   erasable only by ultraviolet rays. EPROMs are programmed using a thermal agitation phenomenon in the conduction channel under the effect of a saturation current, which is irreversible.

EEPROMs are electrically programmable and
15   erasable. EEPROMs are programmed or erased by the tunnel effect. The programming and erasing voltages are usually produced by internal circuits of the memory, such as charge pumps or multipliers.

The paper presented by Canet, Bouchakour,
20   Harabech, Boivin, Mirabel and Plossu at the 43[rd] IEEE symposium on circuits and systems in Lansing, Michigan on August 8-11, 2000 describes an EEPROM cell using a control signal that reduces the electric field of the tunnel oxide during cell programming and erasing.
25   The paper presented by Canet, Bouchakour, Harabech, Boivin and Mirabel at the ISCAS-IEEE

international symposium on circuits and systems in Sydney, Australia describes a control signal enabling a reduction in the programming time. FIGS. 2 and 3 illustrate schematically a memory cell and the voltages applied to its electrodes, respectively during an erasing step and during a programming step. During erasing, the substrate, drain and source are connected to ground, and a positive voltage pulse is applied to the control gate of the memory cell.

The ratio between the floating gate voltage and the control gate voltage is in this case defined by the following formula: $Kc = Cpp/(Cpp+Ctun+Cox)$. Cpp is the coupling capacitance between the control gate and the floating gate, Ctun is the capacitance between the drain and the floating gate, and Cox is the capacitance between the floating gate and the substrate. The tunnel voltage is then defined by $Vtun = Kc * Vg$, where Vg is the voltage applied to the gate.

During programming, the control gate and the substrate are connected to ground, the source is floating, and a positive voltage pulse is applied to the drain. The ratio between the floating gate voltage and the control gate voltage is in this case defined by the following formula: $Kw = Ctun/(Cpp+Ctun+Cox)$. The tunnel voltage is then defined by $Vtun = (1-Kw) * Vd$, where Vd is the drain voltage.

These EEPROMs and their control method have drawbacks. To maintain a same injected charge and similar performance, an optimized control signal implies an increase in the drain or gate biasing voltage. It is difficult to devise a power supply for the memory array which generates a sufficiently high biasing voltage. Moreover, this memory cell is subjected to a tunnel effect phenomenon between conduction bands, known under the acronym BTBT, which

is the source of an increase in the cell's consumption. Moreover, the optimized programming and erasing pulses are difficult to generate and complicate the associated power supply.

5   **Summary of the Invention**

In view of the foregoing background, an object of the present invention is to provide an EEPROM memory control method and a corresponding EEPROM that overcomes the above described drawbacks.

10   The method of the invention, which is also in conformance with the generic definition given in the background section, is essentially characterized in that the state setting step comprises a simultaneous application of opposite polarity voltage pulses

15   respectively to the drain and to the control gate of the floating gate transistor. The pulses may exhibit a first portion exhibiting an edge/slope greater than K*8 MV/s, and a second portion exhibiting an edge/slope between K*1 KV/s and K*1 MV/s, with K=1 when the pulse

20   has a positive polarity and with K=-1 when the pulse has a negative polarity. The pulses may further have a third portion exhibiting a substantially zero slope, and a fourth portion exhibiting an edge/slope of less than K*16 MV/s.

25   At least one state setting step may be a programming step in which the voltage applied to the control gate is negative, and the voltage applied to the drain is positive. At least one state setting step may be an erasing step in which the voltage applied to

30   the control gate is positive, and the voltage applied to the drain is negative. The voltages applied simultaneously to the control gate and to the drain may have a same amplitude.

In one embodiment, the transistor is formed in a substrate, and the method further comprises applying the drain voltage to the substrate, at least during the state setting step of the cell. The polarities of the applied voltages may be defined relative to a reference voltage, and the substrate may have a ground whose voltage is the reference voltage. The amplitudes of the applied voltages may be less than 10 volts. The potential difference between the control gate and the drain is between 12 and 16 volts during the simultaneous application of the voltages.

The cell may additionally include a selection transistor whose source is connected to the drain of the floating gate transistor, and a voltage of less than 12 volts may be applied to the gate of the selection transistor during the programming or erasing step of the cell. The voltage applied to the drain of the selection transistor may exhibit the same polarity as the voltage applied to the drain of floating gate transistor during the state setting step.

The invention also relates to an electronic device comprising at least one EEPROM memory cell and a power supply for the cell for implementing the above-described method. The electronic device may be produced on a P-type substrate. The cell may include a floating gate transistor produced on the surface of a P-type well. The electronic device may also have an N-type isolation well separating the P-type well from the P-type substrate.

Brief Description of the Drawings

The invention shall be better understood upon reading the following description and studying the appended drawings. The figures show:

FIG. 1 is a schematic diagram of a memory cell structure in accordance with the prior art;

FIG. 2 is a schematic diagram showing the erasing voltages applied to a memory cell in accordance with the prior art;

FIG. 3 is a schematic diagram showing the programming voltages applied to a memory in accordance with the prior art;

FIG. 4 is a schematic diagram showing the erasing voltages applied to a memory cell in accordance with the present invention;

FIG. 5 is a schematic diagram showing the programming voltages applied to a memory cell in accordance with the present invention;

FIG. 6 is a graph of an optimized voltage pulse applied to a memory cell electrode during a state setting step; and

FIG. 7 is a cross-sectional diagram of a memory cell structure in accordance with the present invention.

Detailed Description of the Preferred Embodiments

The voltage values indicated below correspond to peak voltages. The invention simultaneously applies voltages of opposite polarities respectively to the drain and to the control gate of the floating gate transistor of an EEPROM memory cell during the state setting step - which is either an erasing step or a programming step. The applied voltages are pulses having an optimized shape, as will be defined in greater detail below. It is thus possible to split the biasing voltage between the control gate and the drain during the state setting step. Moreover, the generation of optimized pulses is facilitated with the

disclosed electronic device in accordance with the
present invention.

FIG. 1 shows an example of a cell structure
of an EEPROM 1. The memory cell has a selection
5 transistor Msel and a floating gate type storage
transistor Mlec. Transistor Msel selectively connects
the drain DF of transistor Mlec to a bit line (not
shown). Transistor Mlec has two stacked gates: a
floating lower gate FG and a control upper gate CG.
10 These two gates are separated by an interpolysilicon
oxide.

Transistor Mlec has a tunnel window tu with a
thickness on the order of 80 nm between the floating
gate FG and the drain DF. The window tu allows a
15 tunnel current to pass between the drain and floating
gate of transistor Mlec when the voltage between the
faces of the tunnel oxide exceeds a critical threshold.
This voltage corresponds to an electric field on the
order of $10*10^6$ V/m. Depending on whether the voltage
20 is positive or negative, the floating gate becomes
positively or negatively charged. The stacking of
gates CG and FG forms a capacitor at the terminals of
which there then appears a permanent potential
difference.

25 The conduction of transistor Mlec depends on
the charge in the floating gate. When transistors Msel
and Mlec are conducting, the current between the source
S of transistor Mlec and the drain DS of transistor
Msel depends on the programming state of the cell
30 determined by the charge. A reference readout voltage
is applied to the gate CG, then the current is measured
and compared with a reference value. The comparison
yields binary information on the cell's programming
state. The reference current corresponds to the
35 current obtained for a threshold voltage devoid of

charge for the EEPROM cell. This voltage corresponds to the case where the floating gate is discharged.

FIGS. 4 and 5 show an EEPROM memory cell comprising a selection transistor Msel, a floating gate
5   storage and readout transistor Mlec, and a substrate B. The floating gate transistor Mlec has a control gate CG, a floating gate FG, a source S and a drain DF. Transistor Msel has a selection gate SG, a drain DS and a source DF connected to the drain of transistor Mlec.

10   The diagrams framed by broken lines correspond to voltages applied to cell electrodes. The erasing and programming steps are the cell's state setting steps. During a state setting step, voltages of opposite polarity are simultaneously applied to the
15   drain and to the control gate of the transistor.

Accordingly, for a predetermined potential difference applied between the control gate CG and the drain DF, there is a reduction in the amplitude of the voltages applied respectively to the control gate CG
20   and to the drain DF. This sharing of the voltages applied to the electrodes during a state setting step allows a power supply for the cells which is less costly and has a lower electrical consumption. It is notably possible to use charge pumps having a lower
25   power at the cell output.

Sharing of the voltages also provides an attenuation or elimination of the tunnel effect by conduction band curvature – also known as BTBT for band-to-band tunneling. Sharing of the voltages
30   further allows the voltage applied to the selection gate of the selection transistor Msel to be reduced if needed. A voltage of less than 12 Volts may be applied to the gate of the selection transistor during the state setting steps.

As can be observed from FIGS. 4 and 5, a
power supply applies a voltage of a given polarity to
the drain DS of transistor Msel. The selection gate SG
receiving a voltage causing transistor Msel to conduct
5   during a state setting step includes applying the same
polarity voltage to the drain DS and to the drain DF of
transistor Mlec.

FIG. 4 shows a memory cell 1 and the voltages
applied to its electrodes during an erasing step. The
10   voltage applied to the control gate CG then passes from
a reference voltage to a positive voltage. The voltage
applied to the drain DS, and hence also the voltage
applied to the drain DF, passes from a reference
voltage to a negative voltage. A positive voltage is
15   thus simultaneously applied to the control gate CG and
a negative voltage to the drain DF.

FIG. 5 shows a memory cell 1 and the voltages
applied to the electrodes during a programming step.
The voltage applied to the control gate CG thereby
20   passes from a reference voltage to a negative voltage.
The voltage applied to drain DS, and hence the voltage
applied to drain DF, passes from a reference voltage to
a positive voltage. There is thus simultaneously
applied a negative voltage to the control gate CG and a
25   positive voltage to drain DF.

The voltages applied to the drain, source,
and control gate or to the substrate during a state
setting step are pulses, and have a timing diagram as
shown in FIG. 6. In the formula that follows, K is a
30   coefficient defined by K=1 when the pulse has a
positive polarity, and K=-1 when the pulse has a
negative polarity. The pulse 2 has a first portion 11
having a slope greater than K*8 MV/s. This slope
enables the tunnel effect to be quickly established in
35   the floating gate transistor. A state setting step can

thus be accelerated. A second portion 12 continues
from the first portion and has a slope between K*1 KV/s
and K*1 MV/s. The second portion serves to set the
tunnel current. The slope in this range is chosen to
5 be substantially proportional to the desired speed of
the cell. When the slope of the second portion is kept
to that range, the reliability of the memory cell is
improved. The transition from the first portion to the
second portion is preferably made just before the flow
10 of tunnel current.

A third portion 13 continues from the second
portion and has a substantially zero slope. This third
portion enables compensation for variations in the
pulse during cell operation. This portion effectively
15 ensures that the first and second portions have been
executed in their entirety. A fourth portion 14
continues from the third portion and has a slope less
than K*16 MV/s. Such a slope is used preferably to
reduce the cell's writing or erasing time.

20 Such pulses are more easily generated when
opposite polarity pulses are simultaneously applied
respectively to the drain and control gate of the
floating gate transistor during a state setting step.
Indeed, since the amplitudes of the voltages applied to
25 these electrodes are more reduced, constraints on the
power supply to generate such slopes are reduced.
Accordingly, for given slopes of part 1 or 4 of the
pulse, a simplified and less costly power structure can
be used.

30 The potential differences between the control
gate CG and drain DF or DS are preferably equal during
a programming step and during an erasing step.
Generally, the voltages used allow for the electric
field in the tunnel oxide to be identical, in absolute
35 value, during the programming and erasing steps. The

voltages on the control gate CG and on drain DF are then adapted as a function of the coupling coefficients respectively in programming and in erasure. It is thus possible to charge the floating gate identically, in

5   terms of absolute value, during a programming step and during an erasing step. The incidence of a loss of charge shall then be identical for the two state setting steps. Moreover, if equal amplitudes are used on the control gate CG and on drain DF, the erasing and

10   programming voltages are centered relative to a readout voltage.

It is also possible to have a state setting step during which the voltages simultaneously applied to the control gate and to drain DF have a same

15   amplitude. This alternative also allows simplification of the power supply. A same voltage source, whose polarity is modified, can then be used to supply the gate CG and drain DF. This alternative also allows voltages of minimal amplitude to be used on the control

20   gate and on the drain DF. Indeed, the amplitude of the voltages applied to the gate CG and to the drain DF is then one half of a predetermined potential difference applied between the control gate CG and the drain DF.

A zero potential difference is also

25   preferably applied between the drain DF or drain DS and the substrate B during a state setting step of the cell. The voltage of the substrate B can notably be the voltage of an N-type isolation well of the substrate. Accordingly, in the case where the drain DS

30   is N-doped and where the isolation well is N-doped, the current consumption on the drain is reduced. Also, during a programming step, a positive voltage is applied to the N-type isolation well of the substrate. This thereby eliminates the substrate effect of the

35   selection transistor Msel, which allows an optimal use

of the output level of a cell power supply pump. Using
the definitions given above for Kc and Kw, the
equations in this case become as follows: $Kc = Cpp/(Cpp+Ctun+Cox)$; and $Kw = (Ctun + Cox)/(Cox+Ctun+Cpp)$

5 since the potential difference between drain DS and the
control gate CG is zero. The relation $Kc + Kw = 1$ is
thus verified for the cell's state setting steps.

The tunnel potential difference Vtun, applied
between the drain DS and the control gate CG, thus

10 verifies the relation $Vtun = Kc*Vg - (1-Kw)*Vd$, then
the relation $Vtun = Kc*(Vg-Vd)$. Vg is the voltage of
the control gate and Vd is the voltage of drain DS.
The latter relation enables the voltages Vd and Vg to
be determined to apply during a state setting step for

15 a predetermined potential difference Vtun.

In the example presented, the source S and
the drain DF are substantially at the same voltage
during the erasing and programming steps. It is also
possible to leave the source S floating during the

20 erasing and programming steps. This alternative allows
a reduction or elimination of perturbations on other
memory cells not selected during the state setting
steps of the cell 1.

To determine the polarity of the voltages

25 applied to cell electrodes, the voltage levels of the
electrodes used during the reading step are used as a
reference level. It is also possible to use the
substrate's ground voltage as a reference voltage.

The invention makes it possible to use

30 voltages below 10 Volts on the control gate and on the
drain DF or drain DS. These voltages enable use of a
cell power supply which is less costly and which has a
lower power consumption, as described above. Such
voltages allow a potential difference Vtun between 12

35 and 16 Volts to be maintained. These voltages

therefore allow a potential difference Vtun substantially equal to those used in the state of the art to be maintained. The electric field generated between the floating gate and drain DF is thus

5   substantially identical to the electric fields generated in the state of the art. The operation of the memory cell is therefore not altered by control gate and drain voltages lower than those used in the state of the art.

10   Tests have been conducted with the following parameters: $|Vg| = 7V$, $|Vd| = 7V$, $|Vsg| = 16V$, $|Vb| = 7V$ and $|Vs| = 7V$ and pulses of 4 millisecond duration. It was observed that the life of the memory cell was not affected by the control method in accordance with the

15   invention.

The invention also relates to an electronic device comprising an EEPROM memory cell and a power supply for the memory cell. The device is configured to implement any one of the described methods in

20   accordance with the invention. FIG. 7 shows schematically an example of a memory cell implementing the invention.

The memory cell comprises a selection transistor Msel, and a storage transistor Mlec. These

25   transistors are produced in a P-type well identified by reference CP. Well zones forming isolation wells NW extend on the periphery of the well CP. The memory cell further comprises an N-type isolation well identified by reference CIN for connecting the wells

30   NW.

Isolation well CIN isolates well CP from a P-type substrate identified by reference SP. Isolation well CIN enables voltages of opposite polarity to be applied to the control gate CG and to the drain DS or

DF.   The power supply of the different electrodes of the memory cell can be adapted to implement these method, as readily understood by those skilled in the art.

5   Although there has been described up to this point a memory cell provided with a floating gate transistor and a selection transistor, the invention is also applicable to a memory cell that does not have a selection transistor.   Moreover, although the erasing

10   and programming polarities described are associated respectively to erasing and programming, these polarities can be swapped.